



DLC3000

P0050F0011



DLC3000

Key benefits

- > Compact control panel for Arrowstick, Sirens, Light Beacon, etc.
- > Complete set of control panel, power module and FTP Bus cable(5m)
- > Control panel features backlighting and label collection



Designers

- > Handbrake-sensitive features
- > Overview siren and flashing light status
- > Overload protection
- > Flood protection
- > Reverse polarity protection
- > Interlock
- > For Arrowstick of 4, 6 or 8 light points (halogen/LED)
- > Push button control
- > Permanent Outputs
- > Various Auto standby modes
- > Compliance: 2004/104/CE
e6 03 0331
ECE R10
- > Supplied materials

9	Vein end sleeve 2.5mm ²	Blue
9	Vein end sleeve 1.5mm ²	Red
1	Diode	MCC 1N4003

Specifications

- > Operational Voltage: from +10 to +28VDC
- > 3 positive outputs (10A each)
- > 8 Arrowstick outputs (2A each)
- > 1 positive IGNITION input
- > 1 negative HANDBRAKEinput
- > Terminal type:

Side power supply	
8 x	0.8x6.35mm
Side FTP	
8 x	Screw clamp 3mm x 0.5mm

- > 1 FTP port for connection to control panel
- > Weight:
Power Module: 80gr.
1,76oz
Control panel: 115gr.
4,06oz
- > Dimensions:
Power Module: 94 x 73 x 26 mm (B x D x H)
3.7 x 2.9 x 1.02" (B x D x H)
Control panel: 95 x 70 x 35 mm (B x D x H)
3,7 x 2,8 x 1,4 inches (B x D x H)
- > Operating temperature: from -25°C to +60°C