



DLC3000 ARISCO

P0050F0011A



DLC3000

Key benefits

- > Compact control panel for Arrowstick, Sirens, Light Beacon, etc.
- > Complete set of control panel, power module and FTP Bus cable(5m)
- > Control panel features backlighting and label collection
- > Additional ARISCO Pattern



Designers

- > Handbrake-sensitive features
- > Overview siren and flashing light status
- > Overload protection
- > Flood protection
- > Reverse polarity protection
- > Interlock
- > For running lights 4, 6 or 8 light points (halogen/LED)
- > Push button control
- > Permanent exits
- > Various Auto standby modes
- > Compliance: 2004/104/CE
e6 03 0331
ECE R10
- > Supplied materials

9	Vein end sleeve 2.5mm ²	Blue
9	Vein end sleeve 1.5mm ²	Red
1	Diode	MCC 1N4003

Specifications

- > Operational Voltage: from +10 to +28VDC
- > 3 positive outputs (10A each)
- > 8 Arrowstick outputs (2A each)
- > 1 positive IGNITION input
- > 1 negative HANDBRAKE input
- > Terminal type:

Side power supply	
8 x	0.8x6.35mm
Side FTP	
8 x	Screw clamp 3mm x 0.5mm
- > 1 FTP port for connection to control panel
- > Weight:

Power Module:	80g.
	1.76oz
Control panel:	115g.
	4.06oz
- > Dimensions:

Power Module:	94 x 73 x 26 mm (B x D x H)
	3.7 x 2.9 x 1.02" (B x D x H)
Control panel:	95 x 70 x 35 mm (B x D x H)
	3.7 x 2.8 x 1.4" (B x D x H)
- > Operating temperature: from -25°C to +60°C